



N8346BS-0250

N Jack Solder Clamp 4-Hole 25.4SQ Flange
For RG401; 18GHz VSWR 1.2

50Ω



MOUNTING HOLE



Parts	Material	Plating (Micro-inch)
Solder Clamp Nut	Brass	Gold 4 Over Nickel-Phosphorus Alloy 80 Over Copper 20
Contact Body	Brass	Gold 4 Over Nickel-Phosphorus Alloy 80 Over Copper 20
Contact Pin	Beryllium Copper	Gold 4 Over Nickel-Phosphorus Alloy 80 Over Copper 20
Insulator	Teflon	
Body	Stainless	Passivated

Weight: 40.82 g

Suitable Cables: Semi-rigid.250

This part number complies with RoHS.






Notice: JYEBAO reserves the right to make modifications deemed appropriate.

N	N8346BS-0250
Interface MIL-STD-348B	
Electrical Data Impedance 50Ω Frequency range DC to 18GHz VSWR ≤ 1.2 (DC to 18GHz) Insertion loss $\leq 0.05 \times \sqrt{f(\text{GHz})}$ dB Insulation resistance $\geq 5000\text{M}\Omega$ Contact resistance inner conductor $\leq 1.5\text{m}\Omega$ Contact resistance outer conductor $\leq 1\text{m}\Omega$ Dielectric withstanding voltage (at sea level) 2500 V rms Working voltage (at sea level) 1000 V rms	
Mechanical Data Recommended coupling nut torque 6 to 10 inch lbs Coupling proof torque 15 inch lbs Contact captivation-axial ≥ 6.3 lbs Durability (mating) ≥ 500	
Environmental Data Temperature range -65°C to +165°C Thermal shock MIL-STD-202, Method 107, Condition B Moisture resistance MIL-STD-202, Method 106 Corrosion MIL-STD-202, Method 101, Condition B RoHS Compliant	
Tooling Locator tool ST-011 Soldering fixture ST-008 Insert for .250 semi-rigid cable ST-250	

Notice: JYEBAO reserves the right to make modifications deemed appropriate.


JYE BAO CO., LTD.

CABLE ASSEMBLY INSTRUCTION

N8346BS-0250		DATE	2020/05/30	REV	—
A  BODY		B  SOLDER NUT			
DIAGRAM		ASSEMBLY INSTRUCTION			
		Step 1: STRIP AS SHOWN. Step 2: SHARPEN CENTER CONDUCTOR TIP.			
		Step 3: USE SOLDERING FIXTURE " ST-008 ", INSERT TOOL " ST-250 " AND LOCATOR TOOL " ST-011 " TO FIX THE NUT " B ". SOLDER IN " X ".			
		Step 4: CUT AWAY ANY EXCESS TEFLON STICKING OUT OF THE SOLDER NUT.			
		Step 5: FINALLY SCREW NUT " B " ON THE CONNECTOR BODY " A ".			
This part number complies with RoHS. Notice: JYEBAO reserves the right to make modifications deemed appropriate.					
APPROVED		CHECKED		DRAWING	
				Albert	

N8346BS-0250

S11



1 S11
13.6641 GHz
-21.05 dB