


SMA8300LS-0405

SMA Jack Solder Bulkhead
For Flexible RG405; 18GHz VSWR 1.2*

50Ω



MOUNTING HOLE

*Using 5002

Parts	Material	Plating (Micro-inch)
Body	Stainless Steel	Passivated
Insulator	Teflon	
Barrel	Brass	Gold 4 Over Nickel-Phosphorus Alloy 80 Over Copper 20
Contact Pin	Beryllium Copper	Gold 4 Over Nickel-Phosphorus Alloy 80 Over Copper 20
Lock Washer	Stainless Steel	Passivated
Hex Nut	Stainless Steel	Passivated

Suitable Cables: 5002; SS405; .085 Flexible; and .085SRF-W-P-50-F

This part number complies with RoHS.





Notice: JYEBAO reserves the right to make modifications deemed appropriate.

SMA		SMA8300LS-0405	
Interface			
MIL-STD-348B			
Mechanically compatible with		2.92 & 3.5	
Electrical Data			
Impedance		50Ω	
Frequency range		DC to 18GHz	
VSWR		≤ 1.2 (DC to 18GHz)	
Insertion loss		$\leq 0.04 \times \sqrt{f(\text{GHz})}$ dB	
Insulation resistance		$\geq 5000\text{M}\Omega$	
Contact resistance inner conductor		$\leq 3\text{m}\Omega$	
Contact resistance outer conductor		$\leq 2\text{m}\Omega$	
Dielectric withstanding voltage (at sea level)		750 V rms	
Working voltage (at sea level)		250 V rms	
Mechanical Data			
Recommended coupling nut torque		7 to 9.5 inch lbs	
Coupling proof torque		15 inch lbs	
Coupling nut retention force		≥ 60.7 lbs	
Contact Captivation-axial		≥ 6.1 lbs	
Durability (mating)		≥ 500	
Environmental Data			
Temperature range		-65°C to +165°C	
Thermal shock		MIL-STD-202, Method 107, Condition B	
Moisture resistance		MIL-STD-202, Method 106	
Corrosion		MIL-STD-202, Method 101, Condition B	
RoHS		Compliant	
Tooling			
Soldering gauge	ST-0.5	Soldering fixture	ST-008
Locator tool	ST-011	Insert for RG405	ST-009

Notice: JYEBAO reserves the right to make modifications deemed appropriate.

JYE BAO CO., LTD.

CABLE ASSEMBLY RECOMMENDATION

SMA8300LS-0405		DATE	2020/06/12	REV	A
A		B			
					
BODY + WASHER + HEX NUT		CONTACT PIN			
DIAGRAM		ASSEMBLY INSTRUCTION			
		Step 1: STRIP AS SHOWN.			
		Step 2: PUT 0.5 MM GAGE ST-0.5 IN PLACE, INSERT CABLE'S CENTER CONDUCTOR INTO CENTER PIN " B " AND SOLDER IN " Y ".			
		Step 3: USE SOLDERING FIXTURE " ST-008 ", INSERT TOOL " ST-009 " AND LOCATOR TOOL " ST-011 " TO FIX THE CONNECTOR. SOLDER IN " X ".			
This part number complies with RoHS. Notice: JYEBAO reserves the right to make modifications deemed appropriate.					
APPROVED		CHECKED		DRAWING	
				Albert	