



SMA8346S-0141

SMA Jack Solder SQ 12.7mm 4 Hole Flange
For RG402; 27GHz VSWR 1.2

50Ω



MOUNTING HOLE :



Parts	Material	Plating (Micro-inch)
Contact Body	Stainless	Gold 5 over Nickel 50 over Copper 50
Contact Pin	Beryllium Copper	Gold 4 Over Nickel-Phosphorus Alloy 80 Over Copper 20
Insulator	Teflon	
Body	Stainless	Passivated

Weight: 3.01 g

Suitable Cables: .141 semi-rigid, .141 conformable

This part number complies with RoHS.






Notice: JYEBAO reserves the right to make modifications deemed appropriate.

SMA		SMA8346S-0141	
Interface			
MIL-STD-348B			
Mechanically compatible with		2.92 & 3.5	
Electrical Data			
Impedance		50Ω	
Frequency range		DC to 27GHz	
VSWR		≤ 1.2 (DC to 27GHz)	
Insertion loss		≤ 0.04 x √f(GHz) dB	
Insulation resistance		≥ 5000MΩ	
Contact resistance inner conductor		≤ 3mΩ	
Contact resistance outer conductor		≤ 2mΩ	
Dielectric withstanding voltage (at sea level)		1500 V rms	
Working voltage (at sea level)		500 V rms	
Mechanical Data			
Recommended coupling nut torque		7 to 9.5 inch lbs	
Coupling proof torque		15 inch lbs	
Contact Captivation-axial		≥ 6.1 lbs	
Durability (mating)		≥ 500	
Environmental Data			
Temperature range		-65°C to +165°C	
Thermal shock		MIL-STD-202, Method 107, Condition B	
Moisture resistance		MIL-STD-202, Method 106	
Corrosion		MIL-STD-202, Method 101, Condition B	
RoHS		Compliant	
Tooling			
Soldering gauge	ST-005	Soldering fixture	ST-008
Locator tool	ST-011	Insert for .141 semi-rigid cable ST-010	
Dielectric insertion tool	ST-004		


Notice: JYEBAO reserves the right to make modifications deemed appropriate.

JYE BAO CO., LTD.

CABLE ASSEMBLY RECOMMENDATION

SMA8346S-0141		DATE	2020/06/10	REV	—
A		B	C		
					
BODY		CONTACT PIN	INSULATOR		
DIAGRAM		ASSEMBLY INSTRUCTION			
		Step 1: STRIP AS SHOWN.			
		Step 2: PUT 0.25 MM GAGE IN PLACE, INSERT CABLE'S CENTER CONDUCTOR INTO CENTER PIN " B " AND SOLDER IN " Y ".			
		Step 3: USE SOLDERING FIXTURE " ST-008 ", INSERT TOOL " ST-010 " AND LOCATOR TOOL " ST-011 " TO FIX THE CONNECTOR. SOLDER IN " X ".			
		Step 4: USE DIELECTRIC INSERTION TOOL " ST-004 " TO INSERT THE TEFLON " C ".			
This part number complies with RoHS. Notice: JYEBAO reserves the right to make modifications deemed appropriate.					
APPROVED		CHECKED		DRAWING	
				Albert	

SMA8346S-0141



Mkr	Trace	X-Axis	Value	Notes
1 ▽	S11	5.4460 GHz	-29.26 dB	
2 ▽	S11	5.4460 GHz	-29.26 dB	
3 ▽	S11	17.8568 GHz	-28.14 dB	
4 ▽	S11	25.4711 GHz	-20.39 dB	